

NB341

Conventional Multi-Tone Horn

The **NB-341 Multi-Tone Horn** is a two-wire appliance that operates on a FACP (fire alarm control panel) or **SFM** (Synchronized Function Module) command to provide audible indication of alarm condition. When the notification appliance emits sound, it indicates the possibility of an emergency situation that requires your immediate attention. The appliances are not to be painted or the finish altered in any way.



Listed

Key Features

- Operates when the supply voltage is connected to the device
- The Multi-Tone Horn can be synchronized by using Wizmart's **SFM Synchronized Function Module** (configured by its DIP selection switches) or by specific FACP signal pattern
- 24 V DC operation
- Adjustable sound level
- Loud sounder output
- Low maintenance
- Easy installation

TECHNICAL SPECIFICATIONS

OPERATING VOLTAGE	DC (16 ~ 33) V
REVERSE CURRENT	40 μ A
ALARM CURRENT @ 24V DC	30 mA
SOUNDER OUTPUT	75 dBs @ 3 m
SOUND TYPE	Horn, Bell, 500Hz Horn, Ca Horn, Slow whoop, Siren, Hi/Lo Switchable
TERMINAL WIRING	18AWG ~ 12AWG (0.82 mm ² ~3.31 mm ²)
OPERATING TEMPERATURE	0 °C ~ +50 °C
OPERATING HUMIDITY	10 % ~ 93 % RH, non-condensing at 38 °C
DIMENSIONS (w x h x d)	(133 x 130 x43) mm
INGRESS PROTECTION RATING	IP-22

ORDER CODE

NB341-R	Wall Mount Multi-Tone - RED
NB341-W	Wall Mount Multi-Tone - WHITE

