ASUS PRIME B860M-A WIFI Intel B860 LGA 1851 (Socket V1) micro ATX

Brand : ASUS Product code: 90MB1JY0-M0EAY0

Product name: PRIME B860M-A WIFI

Intel B860 Chipset, $4 \times DIMM$ slots, max. 256GB, DDR5 Supports up to 8666+MT/s (OC), Non-ECC, Unbuffered , Clocked Unbuffered DIMM (CUDIMM)

ASUS PRIME B860M-A WIFI Intel B860 LGA 1851 (Socket V1) micro ATX:

B860M-A WIFI

ASUS PRIME series motherboards are expertly engineered to unleash the full potential of the latest Intel® Core™ Ultra Processors (Series 2). Boasting a robust power design, comprehensive cooling solutions and intelligent tuning options, the PRIME B860M-A WIFI motherboard provides users and PC DIY builders with a range of performance optimizations via intuitive software and firmware features. It's designed to be Advanced AI PC-ready, offering the power and connectivity needed for demanding AI applications.





Processor		Rear panel I/O ports	
Processor manufacturer * Processor socket * Compatible processor series * Supported processor sockets	Intel LGA 1851 (Socket V1) Intel Core Ultra (Series 2) LGA 1851	USB 3.2 Gen 2 (3.1 Gen 2) Type-A ports quantity * USB 3.2 Gen 2x2 Type-C ports quantity Ethernet LAN (RI-45) ports *	1 1 1
Memory		HDMI ports quantity *	1
Supported memory types * Number of memory slots *	DDR5-SDRAM 4	DisplayPorts quantity WiFi-AP antenna jack	2 1
Memory slots type	DIMM Dual-channel	Network	
Memory channels ECC compatibility Maximum internal memory * Unbuffered memory	Non-ECC 256 GB	Ethernet LAN Ethernet interface type Wi-Fi *	✓ 2.5 Gigabit Ethernet ✓
Storage controllers		Top Wi-Fi standard Wi-Fi standards	Wi-Fi 6E (802.11ax) Wi-Fi 6E (802.11ax)
Supported storage drive types Supported storage drive interfaces Number of HDDs supported	HDD & SSD * M.2, SATA III 4	Bluetooth Bluetooth version	5.3
Number of storage drives supported	1 6	Features	·
RAID support RAID levels	v 0, 1, 5, 10	Motherboard chipset * Audio output channels * Component for *	Intel B860 7.1 channels PC
Graphics		Motherboard form factor *	micro ATX
Parallel processing technology support *	Not supported	Motherboard chipset family * Windows operating systems	Intel
Internal I/O		supported	Windows 10 x64, Windows 11
USB 2.0 connectors * USB 3.2 Gen 1 (3.1 Gen 1) connectors * USB 3.2 Gen 2 (3.1 Gen 2)	1	Expansion slots PCI Express x1 (Gen 4.x) slots PCI Express x16 (Gen 4.x) slots	1
connectors *	1	PCI Express x16 (Gen 5.x) slots	1

Internal I/O		Expansion slots	
Number of SATA III connectors *	4	Number of M.2 (M) slots	2
S/PDIF out connector	✓	1st M.2 largest key size	2280
Front panel audio connector	✓	1st M.2 highest PCI Express generation	5.0
Front panel connector	✓	2nd M.2 largest key size	2280
ATX Power connector (24-pin)	✓	2nd M.2 highest PCI Express	4.0
CPU fan connector	✓	generation	4.0
Number of chassis fan connectors	3	BIOS	
Chassis intrusion connector	✓	BIOS type *	UEFI AMI
Number of COM connectors	1	BIOS memory size	256 Mbit
TPM connector	✓	Packaging data	
Thunderbolt headers	1	Package width	275 mm
12V power connector	✓	Package depth	275 mm
RGB LED pin header	✓	Package height	67.5 mm
Rear panel I/O ports		Package weight	1.44 kg
USB 2.0 ports quantity * USB 3.2 Gen 1 (3.1 Gen 1) Type-A ports quantity *	4	Weight & dimensions	
	2	Width	244 mm
		Depth	244 mm
		Packaging content	
		Cables included	SATA
		Antenna included	✓
		Screws included	✓



4711387806289

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.