



MOTHERBOARD

## **SPECIFICATION**

Model Name	X570-A PRO
CPU Support	Supports 2nd and 3rd Gen AMD Ryzen™ / Ryzen™ with Radeon™ Vega Graphics and 2nd Gen AMD Ryzen™ with Radeon™ Graphics Desktop Processors
CPU Socket	Socket AM4
Chipset	AMD <sup>®</sup> X570 Chipset
Graphics Interface	2 x PCI-E 4.0 x16 slots Supports 2-Way AMD <sup>®</sup> CrossFire™ Technology
Display Interface	HDMI – Requires Processor Graphics
Memory Support	4 DIMMs, Dual Channel DDR4-4400(OC)
Expansion Slots	3x PCIe 3.0 x1 slots
Storage	1 x Lightning M.2 slot (Gen4 x4) + 1 x Turbo M.2 slot (Gen3 x4) 6 x SATA 6Gb/s
USB Ports	2 x USB 3.2 (Gen2, A+C) + 8 x USB 3.2 (Gen1) + 6 x USB 2.0
LAN	Realtek <sup>®</sup> RTL8111H Gigabit LAN
Audio	8-Channel(7.1) HD Audio with Audio Boost 4

#### FEATURE



# DRE 80051



# Lightning Gen4 solution

**Frozr Heatsink Design** 

The latest Gen4 PCI-E and M.2 solution with up to 64GB/s bandwidth for maximum transfer speed.

Designed with the patented fan and double ball bearings to provide best performance for enthusiast gamers and

With premium layout and fully digital power design to support



# **DDR4 Boost**

prosumers.

Core Boost

Advanced technology to deliver pure data signals for the best gaming performance and stability.

more cores and provide better performance.


## Audio Boost 4

Isolated audio with a high quality audio processor for the most immersive gaming experience.

#### Flash BIOS Button

Simply use a USB key to flash any BIOS within seconds, without installing a CPU, memory or graphics card.

#### MULTI-GPU



#### **PCI-E Steel Armor**

Protecting VGA cards against bending and EMI

## **CONNECTIONS**



- 1. Keyboard / Mouse
- 2. USB 3.2 Gen1 Type-A
- 3. LAN Port
- 4. HD Audio Connectors
- 5. Flash BIOS Button

#### 6. USB 2.0 Ports

- 7. HDMI Port
- 8. USB 3.2 Gen2 Ports (Type-A + C)
- 9. USB 3.2 Gen1 Type-A Ports
- 10. Optical S/PDIF out

check for the latest version

ated 2019-07-10,

Jen -















