Anker A2683 Universal Black AC Indoor

Brand : Anker Product code: A2683241

Product name: A2683

Anker Prime Charger, 200W 6-Port GaN Charging Station A2683

Anker A2683 Universal Black AC Indoor:

✓Ultra-Powerful Charger Station: Experience the convenience of powering six devices at once with Anker Prime charging station's ultra-powerful 200W output.

✓ Each USB-C Supports 100W Max: When using two USB-C ports simultaneously, each can provide up to 100W of power, transforming charging times for high-demand devices. Charge two 14" MacBook Pros to 50% in just 28 minutes.

✓ 6 Devices, 1 Charger: Power 6 devices simultaneously in one convenient location, ensuring all your tech is ready and fully charged.

✓ The Charger That Protects: Anker's exclusive MultiProtect and ActiveShield 3.0 system deliver comprehensive safety, continuously monitoring charging temperatures to ensure your devices charge safely.

✓ What You Get: Anker Prime Charger (200W, 6 Ports, GaN), 5 ft AC power cord, welcome guide.

Performance		Power	
Charger compatibility *	Universal	Port 1 output power	22.5 W
Power source type *	AC	Port 2 output power	22.5 W
USB 3.2 Gen 1 (3.1 Gen 1) Type-A ports quantity	2	Port 3 output power Port 4 output power	100 W 100 W
USB Type-C ports quantity	4	Port 5 output power	100 W
Fast charging technology	GaN	Port 6 output power	100 W
Charger type *	Indoor	Output current (5V)	3 A
Number of simultaneously connected devices (max) *	6	Output current (9V)	3 A
connected devices (max)		Output current (12V)	1.5 A
Design		Output current (15V)	3 A
Product colour *	Black	Port 1 output current	3 A
Cable length	1.5 m	Port 2 output current	3 A
Gallium nitride (GaN) transistors	✓	Port 3 output current	5 A
Power		Port 4 output current	5 A
Input voltage	100 - 240 V	Port 5 output current	5 A
Input frequency	50 - 60 Hz	Port 6 output current	5 A
Input current	3.2-2.5 A	Weight & dimensions	
Maximum power	200 W	Width	112 mm
Maximum output voltage	20 V	Depth	76 mm
Minimum output voltage	5 V	Height	35 mm
		Weight	563 g



