

## ASUS PRIME Z890M-PLUS WIFI Intel Z890 LGA 1851 (Socket V1) micro ATX

**Brand :** ASUS

**Product code:** 90MB1J80-M0EAY0



**Product name :** PRIME Z890M-PLUS WIFI

Intel Z890 Chipset, 4 x DIMM slots, max. 192GB, DDR5

[ASUS PRIME Z890M-PLUS WIFI Intel Z890 LGA 1851 \(Socket V1\) micro ATX:](#)

### Z890M-PLUS WIFI

ASUS PRIME series motherboards are expertly engineered to unleash the full potential of the latest Intel® Core™ Ultra Processors (Series 2). Boasting a robust power design, comprehensive cooling solutions and intelligent tuning options, the PRIME Z890M-PLUS WIFI motherboard provides users and PC DIY builders with a range of performance optimizations via intuitive software and firmware features. It's designed to be Advanced AI PC-ready, offering the power and connectivity needed for demanding AI applications.



Processor		Rear panel I/O ports	
Processor manufacturer *	Intel	USB 3.2 Gen 1 (3.1 Gen 1) Type-A ports quantity *	4
Processor socket *	LGA 1851 (Socket V1)	USB 3.2 Gen 2 (3.1 Gen 2) Type-A ports quantity *	1
Compatible processor series *	Intel Core Ultra (Series 2)	USB 3.2 Gen 2x2 Type-C ports quantity	1
Supported processor sockets	LGA 1851	Ethernet LAN (RJ-45) ports *	1
Memory		HDMI ports quantity *	1
Supported memory types *	DDR5-SDRAM	DisplayPorts quantity	1
Number of memory slots *	4	Microphone in	✓
Memory slots type	DIMM	WiFi-AP antenna jack	1
Memory channels	Dual-channel	Network	
Non-ECC	✓	Ethernet LAN	✓
Maximum internal memory *	192 GB	Ethernet interface type	2.5 Gigabit Ethernet
Unbuffered memory	✓	Wi-Fi *	✓
Storage controllers		Top Wi-Fi standard	Wi-Fi 7 (802.11be)
Supported storage drive types	HDD & SSD	Wi-Fi standards	Wi-Fi 7 (802.11be)
Supported storage drive interfaces *	M.2, SATA III	Bluetooth	✓
Number of HDDs supported	6	Bluetooth version	5.4
Number of storage drives supported	9	Features	
RAID support	✓	Motherboard chipset *	Intel Z890
RAID levels	0, 1, 5, 10	Audio output channels *	7.1 channels
Graphics		Component for *	PC
Parallel processing technology support *	Not supported	Motherboard form factor *	micro ATX
Internal I/O		Motherboard chipset family *	Intel
USB 2.0 connectors *	2	Windows operating systems supported	Windows 11
USB 3.2 Gen 1 (3.1 Gen 1) connectors *	2	Expansion slots	
Number of SATA III connectors *	6	PCI Express x16 (Gen 4.x) slots	3
S/PDIF out connector	✓	PCI Express x16 (Gen 5.x) slots	1
Front panel audio connector	✓	Number of M.2 (M) slots	3
ATX Power connector (24-pin)	✓		
CPU fan connector	✓		

Internal I/O		BIOS	
Number of chassis fan connectors	4	BIOS type *	UEFI AMI
Chassis intrusion connector	✓	BIOS memory size	256 Mbit
Number of COM connectors	1	Packaging data	
TPM connector	✓	Package width	275 mm
Thunderbolt headers	1	Package depth	275 mm
12V power connector	✓	Package height	67.5 mm
Rear panel I/O ports		Package weight	1.64 kg
USB 2.0 ports quantity *	2	Weight & dimensions	
		Width	244 mm
		Depth	244 mm
		Packaging content	
		Cables included	SATA
		Screws included	✓



4711387755419

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.

Publication date: 11-OCT-2024. Prints or copies of Information are only valid on the printed Publication date