

MOTHERBOARDS

MAG B860 TOMAHAWK WIFI

STABLE FOUNDATION, DURABLY BUILT







SPECIFICATIONS

Model Name	MAG B860 TOMAHAWK WIFI
CPU Support	Supports Intel [®] Core [™] Ultra Processors (Series 2)
CPU Socket	LGA 1851
Chipset	Intel [®] B860 Chipset
Expansion Slots	1x PCle 5.0 x16 slot, 2x PCle 4.0 x16 slots
Display Interface	1x Thunderbolt [™] 4 (Type-C), 1 x HDMI [™] 2.1 FRL, 1 x DisplayPort 1.4 HBR2 – Requires Processor Graphics
Memory Support	4 DIMMs, Dual Channel DDR5 - 9200+ MT/s (OC)
Storage	1x M.2 Gen5 x4 128Gbps slot
	2x M.2 Gen4 x4 64Gbps slots
	4x SATA 6Gbps ports
USB ports	1 x USB Type-C up to 40Gbps,
	Charging support up to 5V/3A, 15W
	6 x USB 10Gbps (4 Type-A + 2 Type-C)
	2 x USB 5Gbps (2 Type-A)
	8x USB 2.0
LAN	Intel [®] Killer™ E5000B 5G LAN
Wireless /	Intel [®] Killer™ Wi-Fi 7 BE1750x, Bluetooth 5.4
Bluetooth	
Audio	8-Channel (7.1) HD Audio with Audio Boost

FEATURES



Thunderbolt[™] 4 port



Thunderbolt[™] 4 brings Thunderbolt to USB-C at true 40 Gb/s

speeds, 8K display support, Daisy-Chain, Multi-Port Accessory Architecture and USB 4.0 compliant.

EZ PCIe Release

A simple press of a button to effortlessly lock or unlock the PCIe slot, simplifying the installation and removal of the graphics card.



Extended Heatsink Design

MSI extended PWM heatsink and enhanced circuit design ensures even high-end processors to run in full speed.



EZ M.2 Shield Frozr II



Lightning Gen 5

The latest PCIe 5.0 solution with up to 128GB/s bandwidth for maximum transfer speed.

Triple M.2 Connectors





GEN5

т.2

5G Network Solution



Featuring premium 5G LAN to deliver better network experience.

Latest DDR5 Memory



A huge step of DDR performance enhancement with the latest DDR5 memory and MSI Memory Boost technology.

Wi-Fi 7

The latest wireless solution with a new 320MHz channel, achieving a maximum transmission speed of 5.8Gbps, which is 2.4 times faster than Wi-Fi 6/6E.

Audio Boost



Reward your ears with studio grade sound quality for the most immersive audio experience.

CONNECTIONS



- 1. Clear CMOS Button
- 3. USB 2.0 (Flash BIOS Port)
- 5. USB 10Gbps (Type-A)
- 7. Flash BIOS Button
- 9. HDMI™
- 11. USB 10Gbps (Type-A)
- 13. Wi-Fi / Bluetooth

- 2. Display Port
- 4. 5G LAN
- 6. Audio Connectors
- 8. Thunderbolt 4 40Gbps (Type-C) 10. USB 2.0
- 12. USB 10Gbps (Type-C)
- 14. S/PDIF-OUT