ASUS PRIME B860-PLUS WIFI Intel B860 LGA 1851 (Socket V1) ATX

Brand : ASUS

Product code: 90MB1K50-M0EAY0

Product name : PRIME B860-PLUS WIFI

Intel B860 Chipset, 4 x DIMM slots, max. 256GB, DDR5 Support up to 8666+MT/s (OC), Non-ECC, Unbuffered ,Clocked Unbuffered DIMM (CUDIMM)

ASUS PRIME B860-PLUS WIFI Intel B860 LGA 1851 (Socket V1) ATX:

B860-PLUS WIFI

ASUS PRIME series motherboards are expertly engineered to unleash the full potential of the latest Intel® Core[™] Ultra Processors (Series 2). Boasting a robust power design, comprehensive cooling solutions and intelligent tuning options, the PRIME B860-PLUS WIFI motherboard provides users and PC DIY builders with a range of performance optimizations via intuitive software and firmware features. It's designed to be Advanced AI PC-ready, offering the power and connectivity needed for demanding AI applications.






Processor		Rear panel I/O ports	
Processor manufacturer * Processor socket *	Intel LGA 1851 (Socket V1)	USB 3.2 Gen 2 (3.1 Gen 2) Type-A ports quantity *	2
Compatible processor series * Supported processor sockets	Intel Core Ultra (Series 2) LGA 1851	USB 3.2 Gen 2x2 Type-C ports quantity	1
Memory		Ethernet LAN (RJ-45) ports * HDMI ports quantity *	1
Supported memory types *	DDR5-SDRAM	DisplayPorts quantity	1
Number of memory slots *	4	WiFi-AP antenna jack	1
Memory slots type	DIMM	Network	
Memory channels	Dual-channel	Ethernet LAN	1
ECC compatibility Maximum internal memory *	Non-ECC 256 GB	Ethernet interface type	2.5 Gigabit Ethernet
Unbuffered memory	∠30 GB	Wi-Fi *	1
Storage controllers		Top Wi-Fi standard	Wi-Fi 6E (802.11ax)
-		Wi-Fi standards	Wi-Fi 6E (802.11ax)
Supported storage drive types	HDD & SSD	Bluetooth	1
Supported storage drive interfaces *		Bluetooth version	5.3
Number of HDDs supported Number of storage drives supported	4	Features	
RAID support	1	Motherboard chipset *	Intel B860
RAID levels	0, 1, 5, 10	Audio output channels *	7.1 channels
Graphics		Component for *	PC
•		Motherboard form factor *	ATX
Parallel processing technology support *	Not supported	Motherboard chipset family *	Intel
Internal I/O		Windows operating systems supported	Windows 10 x64, Windows 11
USB 2.0 connectors *	1	Expansion slots	
USB 3.2 Gen 1 (3.1 Gen 1)	1	PCI Express x16 (Gen 4.x) slots	4
connectors *	-	PCI Express x16 (Gen 5.x) slots	1
USB 3.2 Gen 2 (3.1 Gen 2) connectors *	1	Number of M.2 (M) slots	2

Internal I/O		Expansion slots	
Number of SATA III connectors *	4	1st M.2 largest key size	2280
S/PDIF out connector	 Image: A set of the set of the	1st M.2 highest PCI Express generation	5.0
Front panel audio connector	 Image: A set of the set of the	2nd M.2 largest key size	2280
Front panel connector	1	2nd M.2 highest PCI Express	
ATX Power connector (24-pin)	✓	generation	4.0
CPU fan connector	✓	BIOS	
Number of chassis fan connectors	4	BIOS type *	UEFI AMI
Chassis intrusion connector	1	BIOS memory size	256 Mbit
Number of COM connectors	1	Packaging data	
TPM connector	v	Package width	377 mm
Thunderbolt headers	1	Package depth	372 mm
12V power connector	 Image: A start of the start of	Package height	302 mm
RGB LED pin header	 Image: A set of the set of the	Package weight	1.66 kg
Rear panel I/O ports		Weight & dimensions	
USB 2.0 ports quantity *	4	Width	305 mm
USB 3.2 Gen 1 (3.1 Gen 1) Type-A ports quantity *	1	Depth	244 mm
		Packaging content	
		Cables included	SATA
		Antenna included	✓

Screws included

1



4711387814697

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.