ASUS PRIME B650M-A WIFI II AMD B650 Socket AM5 micro ATX

Brand: ASUS **Product code**: 90MB1EG0-M0EAY0

Product name: PRIME B650M-A WIFI II

- AMD AM5 Socket: Ready for AMD Ryzen™ 7000 Series Desktop Processors
- Ultrafast Connectivity: Wi-Fi 6, M.2 PCle 5.0, Realtek 2.5Gb Ethernet, USB 3.2 Gen 2 ports, front USB 3.2 Gen 1 Type-C®
- ASUS OptiMem II: Careful routing of traces and vias, plus ground layer optimizations to preserve signal integrity for improved memory overclocking
- Comprehensive Cooling: VRM heatsink, PCH heatsink, hybrid fan headers and Fan Xpert 2+
- Aura Sync RGB Lighting: Onboard Addressable Gen 2 headers and Aura RGB header for RGB LED strips, easily synced with Aura Sync-capable hardware

AMD B650 Micro-ATX motherboard, DDR5, PCle 5.0 M.2 support, Realtek 2.5Gb Ethernet, Wi-Fi 6, DisplayPort, VGA, HDMI®, SATA 6 Gbps, USB 3.2 Gen 2 ports, front USB 3.2 Gen 1 Type-C®, BIOS FlashBack™, Arua Sync





Processor			Rear panel I/O ports	
Processor manufacturer *		AMD	USB 2.0 ports quantity *	4
Processor socket *		Socket AM5	USB 3.2 Gen 1 (3.1 Gen 1) Type-A ports quantity *	2
Compatible processor series *		AMD Ryzen™ 7	USB 3.2 Gen 2 (3.1 Gen 2) Type-A	_
Memory			ports quantity *	2
		-SDRAM	Ethernet LAN (RJ-45) ports *	1
,	4 DIMM		VGA (D-Sub) ports quantity *	1
, , ,		channel	HDMI ports quantity *	1
ECC	✓		DisplayPorts quantity	1
Non-ECC	✓		Headphone outputs	1
	4800, MHz	5000,5200,5400,5600,5800,6000,6200,6400	Line-in	✓
	128 G	В	Microphone in	✓
Unbuffered memory	✓		USB connector type	USB Type-A
Storage controllers			Network	
Supported storage drive types		HDD & SSD	Ethernet LAN	✓
Supported storage drive interfa	ces *	M.2, PCI Express 4.0, PCI Express 5.0, SATA	Ethernet interface type Wi-Fi *	2.5 Gigabit Ethernet
Number of HDDs supported		4	Top Wi-Fi standard	Wi-Fi 6 (802.11ax)
Number of storage drives supported 2		2	Top Will Standard	802.11a, 802.11b, 802.11g, Wi-Fi 4
RAID support RAID levels		√ 0, 1, 10	Wi-Fi standards	(802.11a), Wi-Fi 5 (802.11ac), Wi-F 6 (802.11ax)
		0, 1, 10	Bluetooth	√
Internal I/O			Bluetooth version	5.2
USB 2.0 connectors *		2	Features	
USB 3.2 Gen 1 (3.1 Gen 1) connectors *		2	Motherboard chipset *	AMD B650
Number of SATA connectors		4	Audio output channels *	7.1 channels
Total number of SATA connectors		4	Component for *	PC
S/PDIF out connector		✓	Motherboard form factor *	micro ATX
Audio connector		✓	Motherboard chipset family *	AMD
Front panel connector		✓	Power source type	ATX
ATX Power connector (24-pin)		✓	Windows operating systems	Windows 10. Windows 11
Power fan connector		✓	supported	WINDOWS TO, WINDOWS II
CPU fan connector		✓		

Internal I/O		Expansion slots	
Number of chassis fan connectors Peripheral (Molex) power connectors (4-pin)	3 4	PCI Express x16 (Gen 4.x) slots	3
		BIOS	
EPS power connector (8-pin)	✓	BIOS type *	UEFI AMI
Number of COM connectors	1	BIOS memory size	256 Mbit
TPM connector	✓	Clear CMOS button	✓
12V power connector RGB LED pin header	✓	Weight & dimensions	
	✓	Width	244 mm
		Depth	244 mm
		Packaging content	
		Cables included	SATA
		Bundled software	ASUS Exclusive Software Armoury Crate - Aura Creator - Aura Sync - Fan Xpert 2+ - Power Saving Al Suite 3 - TurboV EVO - DIGI+ VRM - PC Cleaner ASUS CPU-Z MyASUS Norton Anti-virus software (Free Trial version) WinRAR UEFI BIOS ASUS EZ DIY - ASUS CrashFree BIOS 3 - ASUS EZ Flash 3 - ASUS UEFI BIOS EZ Mode



4711387034934

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.